

PVR PROGRAMMING INSTRUCTIONS

Follow the sequence and make changes to read as below. Please make sure that the numbers are correct, e.g. not an 8 instead of a 6.

Please Note: The menus have been condensed, so check and change the blocked options.
After the decoder has finished scanning, do not change channels for 20 minutes so that the frequencies can be stored in the memory.

If Animal Planet is not available check Network 1 setup.

If Fashion is not available check Network 2 setup.

If C&I is not available check Network 3 setup.

If Weather is not available check Network 4 setup.

If ESPNC is not available check Network 5 setup.

If E! is not available check Network 6 setup.

1. MAIN MENU - Go to

- 1 Information Central
- 2 Parental control
- 3 Personalise
- 4 **Advanced Options**

Use arrow button to move yellow bar



Press OK

2. SECURITY CHECK

PIN code

9 9 4 9

3. ADVANCED OPTION - Go to

Network SETUP

Press OK

4. HOME NETWORK

- 1 Network
- 2 LNB power is :
- 3 LNB Mode :
- 4 LNB Lo frequency :
- 5 LNB Hi frequency :

**Dstv IS 7
Controlled
Univ
9 7 5 0
1 0 7 0 0**

Use arrow button to find

Press OK - half line will change to grey - change number and press OK

Press OK - Will ask are you sure - press OK

5. NETWORK SETUP

Press OK

Press P+ to take you to Network 1

6. NETWORK 1

- 1 Signal setup
- 2 Use NIT
- 3 Network Frequency
- 4 Symbol Rate
- 5 FEC
- 6 Polarisation

Enabled

S M A T V

1 1 2 1 0

3 0 0 0 0

Press OK - half line will change to grey - change number and press OK

5/6

Vertical

Press OK - will ask are you sure - press OK

7. NETWORK SETUP

Press OK

Press P+ to take you to Network 2

8. NETWORK 2

- 1 Signal setup
- 2 Use NIT
- 3 Network Frequency
- 4 Symbol Rate
- 5 FEC

Enabled

S M A T V

1 1 2 5 0

3 0 0 0 0

Use arrow button to find

Press OK - half line will change to grey - change number and press OK

5/6

P.T.O.

6 Polarisation Vertical
Press OK - Will ask are you sure - press OK

9. NETWORK SETUP **Press OK**

Press P+ to take you to Network 3

10. NETWORK 3

1 Signal setup	Enabled	Use arrow button to find
2 Use NIT	S M A T V	Press OK - half line will change to
3 Network Frequency	1 1 2 9 0	grey - change number and press OK
4 Symbol Rate	3 0 0 0 0	
5 FEC	5/6	
6 Polarisation	Vertical	

Press OK - Will ask are you sure - press OK

11. NETWORK SETUP **Press OK**

Press P+ to take you to Network 4

12. NETWORK 4

1 Signal setup	Enabled	Use arrow button to find
2 Use NIT	S M A T V	Press OK - half line will change to
3 Network Frequency	1 1 3 3 0	grey - change number and press OK
4 Symbol Rate	3 0 0 0 0	
5 FEC	5/6	
6 Polarisation	Vertical	

Press OK - Will ask are you sure - press OK

13. NETWORK SETUP **Press OK**

Press P+ to take you to Network 5

14. NETWORK 5

1 Signal setup	Enabled	Use arrow button to find
2 Use NIT	S M A T V	Press OK - half line will change to
3 Network Frequency	1 1 3 7 0	grey - change number and press OK
4 Symbol Rate	3 0 0 0 0	
5 FEC	5/6	
6 Polarisation	Vertical	

15. NETWORK SETUP **Press OK**

Press P+ to take you to Network 6

16. NETWORK 6

1 Signal setup	Enabled	Use arrow button to find
2 Use NIT	S M A T V	Press OK - half line will change to
3 Network Frequency	1 1 4 1 0	grey - change number and press OK
4 Symbol Rate	3 0 0 0 0	
5 FEC	5/6	
6 Polarisation	Vertical	

Press YELLOW button on the remote to SCAN ALL NETWORKS